

P.A. High Power Mixer Amplifier

MODEL: ASA-350W

Features:

- **In-built Bluetooth facility.**
- **Active bass and treble control.**
- **LED Array for output level.**
- **Multiple inputs for 5 Mikes / 2 Aux source.**
- **Equipped with 8 Pcs. Toshiba 5200 Transistors**
- **Instant transfer to DC power if AC power fails.**
- **19" Rack Mountable Sturdy Chasis in 3U Height**
- **Preamplifier And Line Out for connecting to a booster amplifier and for recording the programme.**
- **External speaker connections are provided for 4 & 8 Ohms and 70V, 100V line.**
- **Provided with fans to keep the amplifier cool enabling trouble free operations under extreme climate conditions.**
- **Line Input for connecting the output from any external mixer**



Technical Specification:

Power Requirements	AC 220-240 V 50/60 Hz DC 36 V (3 X 12 V CAR BATTERY)
Power Output	350 W (Max.)
Input Channels	5 Mikes 2 Aux. 1 USB Port 1 SD / MMC Card Reader
Frequency Response	50-15000 Hz \pm 3dB
Tone Control	Low : \pm 10dB at 100Hz, Hi : \pm 10dB at 10KHz,
Pre-amp. Output	200mV / 600 Ohms
Line Output	1V/1K Ohms
Signal To Noise Ratio	60dB
Output Taps For	2-4-8 Ohms
Speaker Matching	70V-100V Line
Weight (approx.)	24.000 Kg.